

VOXPRIME

The Telephone Paging Specialists

VOX-100

Wall Mount 70V Telephone
Paging Amplifier with
Night Ringer – 100W



DESCRIPTION

The VOX-100 is undeniably the most cost-effective telephone paging amplifier in its category.

It has all the required features for basic installations such as the night ringer. It is the perfect solution for low cost/high reliability installations.



FEATURES

Built-In Night Ringer	Output fully short circuit protected
Music Input (RCA or Screw Terminal)	Thermal and electronic overload protection
100W RMS Continuous / 160W Paging	Wall Mount & Rack Mount installation
70V Output	Heavy Duty Design
VOX with sensitivity level Control	Made in Canada
Volume, Bass & Treble level controls	5 Years Warranty
Separate level controls for Music & Telephone	UL/CSA Listed
Peak Level Indicator	

SPECIFICATIONS

Power Output:	100 watt RMS Continuous / 160 watt Paging
Distortion:	Less than 1%
Frequency Response:	±3 dB, 100 ~ 20,000Hz
Sensitivity:	TEL: 150mV; MUSIC: 100mV
Inputs:	TEL: 600Ω balanced line, transformer-isolated
	MUSIC: 10kΩ unbalanced, Hi-Z source, RCA jacks or screw terminals
	MUSIC MUTE: Mutes music when shorted
	CONTACT RING: Triggers night ringer when shorted
	TEL RING: Triggers night ringer in response to 90V ring signal
Indicators & Controls:	POWER, PEAK LEVEL AND FAULT LED indicators. MUSIC VOLUME, MUSIC BASS,
	MUSIC TREBLE, TEL VOLUME, TEL BASS, TEL TREBLE, VOX, NIGHT RINGER
Outputs:	OUTPUT (70/25V RMS)
Overload Protection:	Thermal and electronic protection with a 2.5A, 120V ~ slow blow fuse
Power Source:	120V AC, 60Hz
Power Consumption:	176 watts
Finish:	Black powder paint with silver and red lettering
Dimensions:	14-¼" W x 8-3/8" H x 2-3/4" D
Weight:	15 lbs
Environment:	Indoor

OPTIONAL ACCESSORIES

VOX-RMK - Amplifier Rack Mount Kit - 5RU

© 2017 Voxprime, Inc.
Specifications subject to change without notice.